

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-84
Благовещенск (4162)22-76-07
Брянск (4832)69-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Колмна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Россия +7(495)268-04-70

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Казахстан +7(7172)727-132

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Киргизия +996(312)96-26-47

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

<https://zetron.nt-rt.ru/> || znc@nt-rt.ru

Zetron MIC-200-IR3 Fixed Flame Gas Detector



MIC-200-IR3 Fixed Flame Gas Detector

- λ Developed on the principle of three-wavelength infrared detection for high security.
- λ High speed fire response;
- λ Built-in high performance microprocessor;
- λ Excellent resistance to radio frequency and electromagnetic interference;
- λ Reliable system fault self-diagnosis function;
- λ Optional 3-wire current loop and relay;
- λ Patented signal processing algorithm to minimise the possibility of false alarms;
- λ Multi-level sensitivity settings to meet different needs in different environments;
- λ Easy to install with 360 degree detection angle.
- λ ExdIICT6 explosion-proof rating for Zone 1 and Zone 2 hazardous locations.

Parameter

Three-band infrared flame detector parameters

Working voltage	DC24V
Voltage range	DC18-30V
Working current	≤30mA, alarm ≤45mA
Spectral range	4-5um, three IR sensors
Viewing angle range	90°
Detection distance source size (0.3m×0.3m)	N-heptane 50m source size (0.3m×0.3m) Gas oil 50m (source size 0.3m×0.3m) Diesel oil 45m (source size 0.3m×0.3m) Kerosene 45m (source size 0.3m×0.3m) Liquor essence 45m (source size 0.3m×0.3m) Methane 30m (source size 0.5m×0.2m) Paper 30m (source size 0.3m×0.3m)
Response time	5-10s The response time of different media is different
Sensitivity level	5 levels of sensitivity (set by remote control)
Signal output	4-20mA three-wire system output Fault ≤3mA, normal 5mA, alarm 15mA Relay type 2 relays (fire alarm, fault) normally open contact output, contact capacity 30V, 3A
Working temperature	-40℃ ~ 70℃
Working humidity	≤95%RH (no condensation)
Electromagnetic compatibility and environmental test	Meet the requirements of the national GB16838 standard, applicable to high temperature, high salt, high temperature and low temperature environments. Anti-point transient, surge voltage interference, anti-static interference
Explosion-proof certification	Exd II CT6/DIP A20 TA, T6
Degree of protection	IP 66
Shell material	aluminum alloy, surface anti-corrosion paint sprayed plastic
Electrical interface	M20X1.5mm
Meet the standards	GB15631-2008, GB3836-2000 series
Weight	1.7kg

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Россия +7(495)268-04-70

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Казахстан +7(7172)727-132

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Киргизия +996(312)96-26-47

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

<https://zetron.nt-rt.ru/> || znc@nt-rt.ru